

SPECIFICATION SHEET

PRODUCT # : CL-343B-AB

• Step Lights

• Cast Brass

Fixture Specifications:

Housing: Corrosion Resistant Cast Brass.

Faceplate: Diecast solid brass, fitted to housing with silicone "O" ring gasket.

Finish: **AB- Antique Bronze.** Natural toning process. AB finish will vary due to artistic process. Also available in **GM**, and **SI** finishes

Lens: Frosted and heat resistant flat glass.

Socket: Top grade bi-pin socket.

Lamp: 12V T3, 20W max.
Available with no lamp or in LED (2W or 2.5W).
See the Lamp Guide below for more information.

Mounting: Surface mounted, includes mounting plate.

Wiring: Fixture is prewired with a 18-2 SPT1-W direct burial cord. Wire connector sold separately. Silicone filled wire nut (**CX-854**) are available from Corona Lighting.

Gasket: Silicone "O" ring seals face plate to housing providing weather tight protection

Electrical Notes: A remote 12V transformer is required. Options are available from Corona Lighting. Voltage range for LED lamps are 8V-21V. Proper grease/lubricant is suggested on threaded parts during installation process.



Warranty: Limited lifetime warranty on fixture against manufacturer's defects.



Twist To Lock Function
Tool Free relamping.



LED
2W and 2.5W



AVAILABLE LED LAMPS (Corona LED lamps have a five (5) year limited warranty against manufacturer's defects)

LAMP NUMBER	WATTS	BEAM		COLOR & TEMP.	RATED HOURS	HALOGEN EQUIVALENT
		SPREAD	LUMEN			
L-EDT3-2W	2	360°	200	2700K	25,000	20 Watt
L-EDT3-2.5W	2.5	180°	240	2700K	25,000	35 Watt
L-EDT3-2W-3K	2	360°	210	3000K	25,000	20 Watt
L-EDT3-2.5W-3K	2.5	180°	250	3000K	25,000	35 Watt
L-EDT3-AM*	2	360°	170	2000K	25,000	20 Watt

* AM- Amber color
For more additional Lamps, and accessories visit Coronalighting.com

JOB INFORMATION

TYPE: _____ DATE: _____

JOB NAME & ADDRESS: _____

PRODUCT #: _____

TOTAL QUANTITY: _____

LAMP TYPE & WATTAGE: _____

TRANSFORMER: _____

CONTRACTOR: _____

SPECIFIER: _____

• If you are ordering LED lamps you should follow the format below:

• **CL** - **product #** - **lamp** - **wattage**

Example: CL-343B-AB-L-EDT3-2W-3K

CL - **343B-AB** - **L-EDT3** - **2W-3K**

• Corona Lighting reserves the right to make any change and/or improvement to the design and construction of this fixture without further notification.

PRODUCT # : CL-343B-AB

•Step Lights

•Cast Brass

Cable Connector

CX-854 Direct Burial Silicone Filled Wire Nut, Tan

